

HS351S

Wireless family home alarm with intelligent control

Ideal for larger family homes, the HS351S family home alarm comes with accessories to protect three rooms on the ground floor, as well as three entry doors or windows. The included keypad provides sophisticated features such as At Home Zoning Mode for greater peace of mind, and the contactless tags and remote control key fob make it simple to control your alarm system.



Pack Contents:

1 x Wireless Keypad, 1 x Wireless Battery Siren, 3 x Wireless Motion Sensor (PIR), 3 x Wireless Door and Window Sensor, 1 x Wireless Remote Control Key Fob, 2 x Contactless Tags, 1 x 4 colour dot stickers for Contactless Tag ID, 3 x Security Window Stickers, 8 x LR6 (AA) 1.5V Battery, 4 x LR20 (D) 1.5V Battery, 9 x LR03 (AAA) 1.5V Battery, 4 x CR2032 (3V) Battery, 1 x Quick Start Guide, 1 x Safety & Guarantee, 1 x Declaration of Conformity,

Key Features and Benefits:

Home Alarm Kits - Easy and convenient to use, these Home Alarm Kits have been designed with your family in mind. This kit includes both a siren and a wireless keypad, as well as the incredibly convenient contactless tags and a remote control key fob.

Peace of mind - Sleep soundly safe in the knowledge that your family and home are protected at night with At Home Zoning Mode, which protects important entry points while still allowing you to move around the house. Should anything happen while you're away, Event and Tamper Alerts will let you know if the alarm has been triggered or tampered with. Your keypad will even alert you if you've left a window or door open when you try to arm your Honeywell home alarm.

Easy to use - The entire family can arm and disarm your Honeywell home alarm with ease by using the keypad and contactless tags, or if using the remote control key fob, from up to 150m away. For additional peace of mind, there's even a panic button you can use to activate your alarm in case of emergencies.

Easy to maintain - With a long battery life of up to two years, you won't need to worry about your Honeywell Home Alarm after you have installed it. Conveniently located low battery indicators on each accessory will notify you when it's finally time to change the batteries, and the easy-open battery compartments makes the process as easy as 1-2-3.

Reliability and quality - Honeywell ActivLink®, using the 868MHz frequency, is our innovative wireless protocol which delivers greater range capability of up to 200m, extended battery life of up to 2 years, and improved connection reliability with no false triggering, all supported by our 2 year product quality guarantee.

Flexible and expandable - Add up to 44 accessories or devices to your system, and activate and control up to 3 separate zones to suit your lifestyle and needs. You can even link any number of Honeywell Doorbells to your Honeywell Home Alarm to function as additional internal sirens.

Easy To Install - Honeywell Home Alarm Kits have been designed to be easily installed, with all the accessories pre-linked and ready to go out of the box. All fixings and batteries are also included, so there's nothing more to buy, and there's even optional screw-free installation on most accessories with the included sticky pads. All this is backed up by our 2 year product guarantee.

Specification:

Wireless Keypad	
Colour	White
Wall mounted	Yes
Frequency / Wireless Range*	868MHz / 125m
Audible Range (Volume)	150m (94dB)
Melodies	3
Sound	Internal Siren
Alarm Time (minutes)	1
Visual Alerts	LED Indicator
Power	Battery: 8 x LR6 (AA) 1.5V - (included)
Battery Life (Years)	1
Battery Features	Low Battery Indicator
Mains Power via Micro USB	Optional external supply USB 5V 500mA
Maximum Device Capacity	18 x Wireless Motion Sensor (PIR)/Wireless Door and Window Sensor, 8 x Contactless Tag, 5 x Wireless Remote Control Key Fob, 2 x Wireless Motion Sensor (IP54), 2 x Wireless Push Button
Security Features	3 Security Zone / Auto Reset / Open Door/Window Warning / Event Alerts /30s Entry/Exit Delay / Siren Service Mode
Keypad Features	Capacitive Touch Panel Interface / Backlit Buttons / Contactless Tag RFID Reader / Programmable 4 digit user access code / Built in doorbell feature / Compatible with Doorbell and Push Button
Security Functions	Delay Arm/Disarm/Home mode/Panic Alarm
Tamper Protection	Yes
Factory Reset	Yes
Operating Temperature/Storage Temperature	0°C to +40°C/-20°C to +60°C
Dimensions (mm) / Weight (g)	150 (h) x 140 (w) x 30 (d) / 326 (g)
Fixings	Brackets / Rawl Plugs / Screws

Wireless Battery Siren	
Colour	White
Wall mounted	Yes
Frequency / Wireless Range*	868MHz / 200m
Audible Range (Volume)	250m (105dB)
Melodies	1
Alarm Time (minutes)	1 or 3 (Control Unit mode), 3 or 10 (Siren mode)
Visual Alerts	Comfort LEDs
Power	Battery: 4 x LR20 (D) 1.5V - (included)
Battery Life (Years)	1.5
Battery Features	Low Battery Indicator
Maximum Device Capacity	12 x Wireless Motion Sensor (PIR)/Wireless Door and Window Sensor, 6 x Wireless Remote Control Key Fob (Control Unit mode)
Security Features	Control Unit Mode: 1 Security Zone /Alarm Lockout /Auto Reset / Event Alerts /15s Entry/Exit Delay, + Siren Service Mode
Security Functions	Arm/Disarm/Delay Arm/Panic Alarm (Control Unit mode)
Tamper Protection	Yes
Factory Reset	Yes
IP Rating	IP44
Operating Temperature/Storage Temperature	-20°C to +50°C/-20°C to +60°C
Dimensions (mm) / Weight (g)	297 (h) x 190 (w) x 108 (d) / 1270 (g)
Fixings	Brackets / Rawl Plugs / Screws

Wireless Motion Sensor (PIR) (x 3)

Colour	White
Wall mounted	Yes
Screwless mounting option (Sticky pads)	Yes
Frequency / Wireless Range*	868MHz / 200m
Power	Battery: 3 x LR03 (AAA) 1.5V - (included)
Battery Life (Years)	2
Battery Features	Low Battery Indicator / Easy Open Battery Compartment
Detection Range / Angle	12m / 105°
Test Mode	Yes
Tamper Protection	Yes
Operating Temperature/Storage Temperature	0°C to +40°C/-20°C to +60°C
Dimensions (mm) / Weight (g)	81 (h) x 61 (w) x 48 (d) / 75 (g)
Fixings	Brackets / Rawl Plugs / Screws / Sticky Pads

Wireless Door and Window Sensor (x 3)

Colour	White
Wall mounted	Yes
Screwless mounting option (Sticky pads)	Yes
Frequency / Wireless Range*	868MHz / 200m
Power	Battery: 1 x CR2032 (3V) - (included)
Battery Life (Years)	2
Battery Features	Low Battery Indicator / Easy Open Battery Compartment
Test Mode	Yes
Tamper Protection	Yes
Operating Temperature/Storage Temperature	0°C to +40°C/-20°C to +60°C
Dimensions (mm) / Weight (g)	71 (h) x 40 (w) x 14 (d) / 28 (g)
Fixings	Screws / Sticky Pads

Wireless Remote Control Key Fob

Colour	Black
Frequency / Wireless Range*	868MHz / 150m
Visual Alerts	Confidence Light
Power	Battery: 1 x CR2032 (3V) - (included)
Battery Life (Years)	2
Battery Features	Low Battery Indicator / Easy Open Battery Compartment
Security Functions	Delay Arm/Disarm/Home mode/Panic Alarm (with Keypad) or Arm/Disarm/Delay Arm/Panic Alarm (with Siren)
Operating Temperature/Storage Temperature	0°C to +40°C/-20°C to +60°C
Dimensions (mm) / Weight (g)	62 (h) x 33 (w) x 14 (d) / 16 (g)

Contactless Tag (x 2)

Colour	Black
Frequency / Wireless Range*	125kHz
Operating Temperature/Storage Temperature	0°C to +40°C/-20°C to +60°C
Dimensions (mm) / Weight (g)	36 (h) x 24 (w) x 5 (d) / 7 (g)

Pack

EAN Code	5004100966599
Pack Dimensions (mm) / Weight (g)	320 (h) x 177 (w) x 320 (d) / 4900 (g)
Standard Pack Quantity	3

* Measured in open field conditions, walls, ceilings and metal structures will reduce the maximum range.

livewell.honeywell.com | © 2015 Honeywell International Inc.